

Virtex-4	FPGA	Speed Grades (slowest to fastest)	Slices or LE's	FF's	Gate Estimate		Max I/O's	FF's in I/O pad	Multipliers (18x18)	PowerPC Blocks	Memory			
					Max (100% util)* (1000's)	Practical (60% util)* (1000's)					Blocks (18kbits)	Total (kbits)	Total (kbytes)	
					LX	LX100					-10,-11,-12	49,152	98,304	1,380
	LX160	-10,-11,-12	67,584	135,168	1,890	1,130	960	10	96	0	288	5,184	648	
	LX200	-10,-11	89,088	178,176	2,490	1,490	960	10	96	0	336	6,048	756	
	FX	FX40	-10,-11,-12	18,432	36,864	520	310	448	10	32	2	144	2,592	324
		FX60	-10,-11,-12	25,280	50,560	710	430	576	10	128	2	232	4,176	522
		FX100	-10,-11,-12	42,176	84,352	1,180	710	768	10	160	2	376	6,768	846
		FX140	-10,-11	63,168	126,336	1,770	1,060	896	10	192	2	552	9,936	1,242